



Customers may choose to change local preference for their routes.

Community	Local-Pref	Description
(default)	500	Customer default
16904:70	70	Customer least preferred
16904:80	80	Customer alternate backup
16904:90	90	Customer backup
16904:666		Blackhole

Customers may choose to prepend to all Arvig eBGP peers.

Community	Description
16904:11000	Prepend 1x to all peers
16904:12000	Prepend 2x to all peers

Customers wanting to alter route announcements to selected peers

Community	Description
16904:10001	No-Export to all Telia peers
16904:10002	No-Export to all Hurricane Electric peers
16904:11001	Prepend 1x to Telia at all POP locations
16904:12001	Prepend 2x to Telia at all POP locations
16904:11002	Prepend 1x to Hurricane Electric at all POP locations
16904:12002	Prepend 2x to Hurricane Electric at all POP locations



Customers wanting to alter route announcements to all peers in selected POPs

Community	Description
16904:10010	No-Export to all peers in the Minneapolis MN 511 POP
16904:10020	No-Export to all peers in the Farnam NE POP
16904:11010	Prepend 1x to all Transit Providers in Minneapolis MN 511 POP
16904:12010	Prepend 2x to all Transit Providers in Minneapolis MN 511 POP
16904:11020	Prepend 1x to all Transit Providers in Farnam NE POP
16904:12020	Prepend 2x to all Transit Providers in Farnam NE POP